

(3 Hours)

Total Marks: 80

**NB:** (1) Question No. 1 is compulsory(2) Answer any **THREE** questions out of the remaining **FIVE** questions.(3) Assume suitable data if **necessary** and **justify** them(4) **Figure** to the **right** indicates **marks**

- 1 (a) What are the main factors which decide the choice of electrical drive for a given application? 5
- (b) State and explain with neat sketches the three main classes of motor duty cycle 5
- (c) With speed torque characteristics, explain the stator voltage control of induction motor. 5
- (d) Compare vector control and direct torque control of an induction motor 5
- 2 (a) Choose an application and explain with neat diagrams the multi quadrant operation of an electrical drive. Mention the speed torque conventions in all the four quadrants. 10
- (b) A drive has the following equations for motor torque (T) and load torque ( $T_l$ ).  $T = -1-2\omega_m$ ;  $T_l = -3\sqrt{\omega_m}$  where  $\omega_m$  is the motor speed in rad/s. Obtain the equilibrium points and determine their steady state stability. 10
- 3 (a) Derive the thermal model of motor for heating and cooling and draw the heating and cooling curves. 10
- (b) Half hour rating of a motor is 200 kW. Heating time constant is 80 min. The maximum efficiency occurs at 75% of full load. Determine the continuous duty rating of the motor. 10
- 4 (a) With a neat block diagram explain closed loop speed control with an inner current control loop in an electric drive. 10
- (b) Draw the circuit diagram of a four quadrant chopper drive for a DC separately excited motor and explain in detail its operation with necessary diagrams in forward motoring mode and regenerative braking mode. 10
- 5 (a) With the speed torque characteristics explain V/f control of induction motor. In the speed torque characteristics, include the region below base speed as well as above base speed. 10
- (b) A 3-phase, 440 volt, 50 hertz, 6 pole star connected induction motor has following parameters referred to stator:  $R_s = 0.5 \Omega$ ,  $R_r' = 0.6 \Omega$ ,  $X_s = X_r' = 1 \Omega$ . Stator to rotor turns ratio is 2. If the motor is used for the regenerative braking, determine
- (i) Maximum overhauling torque it can hold and the range of speed in which it can operate safely.
- (ii) The speed at which it will hold a load with a load torque of 160 N-m 10
- 6 (a) Draw the block diagram and explain in brief the direct torque control of three phase induction motor. What is voltage vector switching table? 10
- (b) What do you mean by vector control or field oriented control of induction motor? Explain with necessary phasor diagram the working principle of vector control 10